

Recharge Request:

Parameters:

- Username
- Password
- Amount
- OperatorCode (See **Appendix I**)
- Number
- ClientId (Unique Client Id)
- CircleCode (See **Appendix II**) (only for mobile recharge for all other pass "*" as circlecode)

Recharge Request Format:

`http://yourdomain.com/RechargeApi/Recharge.aspx?Username=<username>&Password=<APIPassword>&Amount=<Amount>&OperatorCode=<operatorCode>&Number=<number>&ClientId=<your refId>&CircleCode=<circleCode>`

Sample Recharge Request:

`http://yourdomain.com/RechargeApi/Recharge.aspx?Username=user123&Password=123&Amount=10&OperatorCode=1&Number=1234567890&ClientId=10001&CircleCode=12`

Recharge Response Format:

`<RequestStatus>|<TransactionId>|<ClientId>|<OperatorRef>|<RechargeId>|<ErrorCode>|<ResponseMessage>`

Sample Response:

`0|232432|6|Success`

- 0 – Success**
- 2- In Process**
- 1 - Failure**

Status Url Parameter: (if transaction is in pending we call this url to update on your website)

Please set the status url for the recharge request to the login panel.

In Message you will get the following response in POST method:

- <RequestStatus>|<TransactionId>|<ClientId>|<OperatoRef>|<RechargeId>|<ErrorCode>|<ResponseMessage>

Sample Url Format:

<http://www.yourdomain.com/pagename?Message=<message>>

Balance Check Request:

Balance Request Format:

`http://yourdomain.com/RechargeApi/Balance.aspx?Username=<username>&Password=<APIPassword>`

Balance Response Format:

`0|Balance|Message`

Check Transaction Status:

Request Format:

`http://yourdomain.com/RechargeApi/RechargeStatus.aspx?Username=<username>&Password=<APIPassword>&ClientId=<ClientId>`

Response Format:

`<RequestStatus>|<TransactionId>|<ClientId>|<OperatoRef>|<RechargeId>|<ErrorCode>|<ResponseMessage>`

APPENDIX I
OPERATOR CODE

Operator	Code
Airtel	1
Vodafone	2
BSNL 3G	3
BSNL STV	4
BSNL Topup	5
BSNL Recharge	6
Reliance CDMA	7
Reliance GSM	8
Aircel	9
Idea	10
Tata Indicom	11
Loop Mobile	12
Tata Docomo	13
Tata Docomo Special	14
Virgin CDMA	15
Virgin GSM	16
MTS	17
Uninor	18
Uninor Special	19
Videocon	20
Videocon Special	21
MTNL Topup	22
MTNL Recharge	23
T24	24
T24 Special	25
Tata Sky	31
Reliance Digital TV	32
Videocon D2h	33
Airtel Digital TV	34
Dish TV	35
Sun Direct	36
Airtel Postpaid	41
Idea Postpaid	42
Reliance CDMA Postpaid	43
Reliance GSM Postpaid	44
Docomo Postpaid	45
Loop Mobile Postpaid	46
BSNL Postpaid	47
Vodafone Postpaid	48
Tata Indicom Postpaid	49
Tata TeleServices Postpaid	50
BSES Rajdhani	61

BSES Yamuna	62
North Delhi Power Limited	63
Reliance Energy (Mumbai)	64
Mahanagar Gas Limited	65
ICICI Prudential Life	66
Tata AIG Life	67
Airtel Landline	68

**APPENDIX II
CIRCLE CODE**

Operator	Code
Andhra Pradesh	13
Assam	24
Bihar & Jharkhand	17
Chennai	7
Delhi	5
Gujarat	12
Haryana	20
Himachal Pradesh	21
Jammu & Kashmir	25
Karnataka	9
Kerala	14
Kolkata	6
Maharashtra	4
Madhya Pradesh & Chhattisgarh	16
Mumbai	3
North East	26
Orissa	23
Punjab	1
Rajasthan	18
Tamil Nadu	8
Uttar Pradesh – East	10
West Bengal	2
Uttar Pradesh – West	11